

Market Rule Amendment Proposal Form

Part 1 - Market Rule Information

Identification No.:	MR-00487-R00
Subject:	Syncrophasor Data Requirements
Title:	Syncrophasor Data Requirements
Nature of Proposal:	<input checked="" type="checkbox"/> Alteration <input type="checkbox"/> Deletion <input checked="" type="checkbox"/> Addition
Chapter:	4
Appendix:	4.15, 4.24
Sections:	Chapter 4, Section 7.2; Appendix 4.15, Appendix 4.24
Sub-sections proposed for amending:	<ul style="list-style-type: none">• Addition of Section 7.2.1 to Chapter 4.• Appendix 4.15-Amended the section on Syncrophasor Data Requirements for Generation Facilities.• Appendix 4.24-added "SCADA" to the table headings to now read: SCADA Information Requirements; added a table section on Syncrophasor Data Requirements for Electricity Storage Facilities.
Current Market Rules Baseline:	

Part 2 - Proposal History

Version	Reason for Issuing	Version Date
1.0	Draft for Stakeholder Review	December 08, 2025

Approved Amendment Publication Date:

Approved Amendment Effective Date:

Part 3 - Explanation for Proposed Amendment

Discussion

Part 4 - Proposed Amendment

Chapter 4

7. Provision of Connection-Related Information

7.2 ~~[Intentionally left blank]~~ Synchrophasor Data Requirements

7.2.1 Each generator, transmitter and electricity storage participant identified in Appendices 4.15, 4.16 and 4.24 respectively, shall install and maintain at their own expense, synchrophasor data generating devices and associated infrastructure including transformers and communications channels and provide synchrophasor data in accordance with the applicable market manual and the applicable Appendix.

Appendix 4.15-IESO Monitoring Requirements: Generators

Type	Synchrophasor Data Requirements
Generation facility	The following are required unless otherwise specified by the IESO-A p For Aall three phases of the voltage and current phasor measurements and frequency datameasurementsP, as further described in the applicable market manual, shall be required for each generation unit as outlined below: (1) Measured from the generator terminal fFor For-generation generation units with a name-plate rateding greater than or equal to 100 MVA (name-plate rating), measured from the generation facility side of the connection point to the IESO-controlled grid.generator terminal, each generation unit shall provide positive sequence voltage phasor, positive sequence current phasor and frequency from generator terminal.

Type	Synchrophasor Data Requirements
	<p>(2) Measured from the generation facility side of the connection point to the IESO-controlled grid. For generation units connected to the IESO-controlled grid through a common connection point, whose aggregated name-plate rating size is greater than or equal to 100 MVA (aggregate nameplate rating), measured from the generation facility side of the connection point to the IESO-controlled grid positive-sequence voltage phasor, aggregated positive-sequence current phasor and frequency shall be provided from the generation facility side of the connection point to the grid.</p> <p>(3) Measured from the terminals defining the Interconnection Reliability Operating Limit (IROL). For generation units, regardless of rated size, whose output power flow is a part of an Interconnection Reliability Operating Limit (IROL, measured from the terminals defining the Interconnection Reliability Operating Limit), definition, positive-sequence voltage phasor, positive-sequence current phasor and frequency shall be provided at the terminals defining the IROL.</p> <p>(4) Notwithstanding the foregoing, a market participant is not required to measure and provide such data when exempted from such requirement as determined in accordance with <u>comply as per the applicable market manual.</u></p>

~~Unless otherwise specified by the IESO, synchrophasor data requirements shall comply with the corresponding Market Manual.~~

Appendix 4.24-IESO Monitoring Requirements: Electricity Storage Participants

The following information, as a minimum, shall be available on a continual basis to the IESO from:

- (a) any *electricity storage participant* (i) whose *electricity storage facility* is connected to the *IESO-controlled grid*, or (ii) that is participating in the *IESO-administered markets*; and
- (b) any *embedded electricity storage participant* (i) that is not a *market participant* or whose *embedded electricity storage facility* is not associated with any *resources*; (ii) whose *embedded electricity storage facility* includes an *electricity storage unit* with an *electricity storage unit* size rated at greater than 20 MVA or that comprises multiple *electricity storage units*, the aggregated *electricity storage unit* size ratings of which exceeds 20 MVA; and (iii) that is designated by the IESO for the purposes of section 7.3.1 of this Chapter as being required to provide such data in order to enable the IESO to maintain the *reliability* of the *IESO-controlled grid*.

	SCADA INFORMATION REQUIREMENTS
Major electricity storage facility	<p>Monitored Quantities</p> <ol style="list-style-type: none"> 1. Active Power (MW) and Reactive Power (MX) injected or withdrawn <ol style="list-style-type: none"> a) The standard requirement for active and reactive power is the provision of <i>net MW</i> and <i>net MX</i> or <i>gross MX</i>. <i>Gross MW</i> and <i>gross MX</i> or <i>net MX</i> are also to be provided, if designated by the <i>IESO</i> as required for: <ol style="list-style-type: none"> (i) determination of operating <i>security limits</i>; (ii) to maintain <i>reliable</i> operation of the <i>IESO-controlled grid</i>; (iii) for compliance monitoring purposes; or (iv) if provision of only the standard requirement values as defined above would have a negative impact on other <i>market participants</i> through reduced operating <i>security limits</i>. b) For <i>electricity storage units</i> with an <i>electricity storage unit size</i> greater than or equal to 100 MVA, the standard requirement as defined in part a) for each <i>electricity storage unit</i> shall be provided, and <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> for each <i>electricity storage unit</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a). c) For <i>electricity storage units</i> with an <i>electricity storage unit size</i> of less than 100 MVA: <ol style="list-style-type: none"> (i) for a group of <i>electricity storage units</i> if those <i>electricity storage units</i> are similar in size and operating characteristics, the standard requirement as defined in part a) shall be provided as a total for these <i>electricity storage units</i>, and total <i>gross MW</i> and <i>gross MX</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a); or (ii) if designated by the <i>IESO</i> as required for determination of operating <i>security limits</i> or to maintain reliable operation of the <i>IESO-controlled grid</i> or for compliance monitoring purposes, the standard requirement as defined in part a) for each <i>electricity storage unit</i> shall be provided, and <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> for each <i>electricity storage unit</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a). d) For <i>electricity storage facilities</i> that have been aggregated pursuant to Chapter 7 section 2.3: <ol style="list-style-type: none"> (i) the standard requirement as defined in part a) shall be provided as an aggregated total, and an aggregated total <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a); or (ii) if so designated by the <i>IESO</i> as required for determination of operating <i>security limits</i> or to maintain <i>reliable</i> operation of the <i>IESO-controlled grid</i> or for dispatch compliance monitoring purposes, the standard requirement as defined in part a) for each <i>electricity storage unit</i> shall be provided, and <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> for each <i>electricity storage unit</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a).

	SCADA INFORMATION REQUIREMENTS
	<p>2. State of Charge and Charge Limit</p> <p>a) For each <i>electricity storage unit</i> or <i>electricity storage facility</i>, the <i>state of charge</i> of the applicable <i>electricity storage unit</i> or <i>electricity storage facility</i></p> <p>b) For each <i>electricity storage unit</i> or <i>electricity storage facility</i>, the economic maximum charge limit and the economic minimum charge limit expressed in MWh as per the applicable <i>market manual</i>.</p> <p>3. Base point</p> <p>a) For each <i>electricity storage unit</i> or <i>electricity storage facility</i> associated with a <i>resource</i> providing <i>regulation</i>, the basepoint, if applicable, of the <i>electricity storage unit</i> expressed in MW, according to the applicable <i>market manual</i>.</p> <p>4. Dynamic Maximum and Minimum Power</p> <p>a) For each <i>electricity storage unit</i> or <i>electricity storage facility</i>, the economic maximum power mode and economic minimum power mode, expressed in MW.</p> <p>5. Voltage:</p> <p>a) For each <i>electricity storage unit</i>, unit terminal voltage, except if <i>electricity storage units</i> are connected to a common low voltage bus section, then the bus section voltage is adequate for those <i>electricity storage units</i>.</p> <p>6. Equipment Status</p> <p>a) Voltage Control status and stabilizer status (if applicable) for each <i>electricity storage unit</i> with an <i>electricity storage unit size</i> > 100 MVA. When applicable, stabilizer status reporting is only required if it can be switched off by electricity storage participant personnel remotely or at the facility.</p> <p>b) AGC status for each <i>electricity storage unit</i> associated with a <i>resource</i> providing <i>regulation</i>.</p> <p>c) Voltage control status and stabilizer status (if applicable) for each <i>electricity storage unit</i> with an <i>electricity storage unit size</i> < 100 MVA if the status of this equipment is designated by the IESO as required for determination of operating security limits or to maintain reliable operation of the <i>IESO-controlled grid</i>. When applicable, stabilizer status reporting is only required if it can be switched on or off by market participant operating personnel remotely or at the <i>facility</i>.</p> <p>d) Synchronizing Breaker status for each <i>electricity storage unit</i>. Where a <i>electricity storage facility</i> is designed such that no low voltage synchronizing breaker is installed for each <i>electricity storage unit</i>, the status of the appropriate HV breaker(s) and disconnect switch(es) normally used to isolate the electricity storage unit must be provided. Where this results in access to the majority of breakers on a bus, the status of the remainder of the breakers shall be provided to complete the bus configuration.</p> <p>e) Where a <i>electricity storage facility</i> is designed such that there are disconnect switches in parallel, or directly in series, with the synchronizing breaker, the status of those switches is also required.</p>

TYPE	SCADA INFORMATION REQUIREMENTS
	f) <i>Remedial Action Scheme</i> status for each applicable <i>electricity storage unit</i> .
Significant electricity storage facility and minor electricity storage facility connected to IESO-controlled grid	<p>Monitored Quantities</p> <ol style="list-style-type: none"> 1. Active Power (MW) and Reactive Power (MX) injected or withdrawn: <ol style="list-style-type: none"> a) The standard requirement for active and reactive power is the provision of <i>net MW</i> and <i>net MX</i> or <i>gross MX</i> facility. <i>Gross MW</i> and <i>gross MX</i> or <i>net MX</i> are also to be provided, if designated by the IESO as required for: <ol style="list-style-type: none"> (i) determination of operating security limits; (ii) to maintain reliable operation of the <i>IESO-controlled grid</i>; (iii) for compliance monitoring purposes; or (iv) if provision of only the standard requirement values as defined above would have a negative impact on other <i>market participants</i> through reduced operating security limits. b) For <i>electricity storage facilities</i> that have not been aggregated pursuant to Chapter 7 section 2.3: <ol style="list-style-type: none"> (i) for a group of <i>electricity storage units</i> if those <i>electricity storage units</i> are similar in size and operating characteristics, the standard requirement as defined in part a) shall be provided as a total for these electricity storage units, and total <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> shall be provided if designated by the IESO as required using the criteria listed above in part a); (ii) if designated by the IESO as required for determination of operating security limits or to maintain reliable operation of the IESO-controlled grid or for compliance monitoring purposes, the standard requirement as defined in part a) for each electricity storage unit shall be provided, and gross MW and gross or net MX for each electricity storage unit shall be provided if designated by the IESO as required using the criteria listed above in part a). c) For <i>electricity storage facilities</i> that have been aggregated pursuant to Chapter 7 section 2.3: <ol style="list-style-type: none"> (i) the standard requirement as defined in part a) shall be provided as an aggregated total, and an aggregated total <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> shall be provided if designated by the IESO as required using the criteria listed above in part a); or (ii) if so designated by the IESO as required for determination of operating security limits or to maintain reliable operation of the IESO-controlled grid or for dispatch compliance monitoring purposes, the standard requirement as defined in part a) for each electricity storage unit shall be provided, and <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> for each <i>electricity storage unit</i> shall be provided if designated by the IESO as required using the criteria listed above in part a). 2. Voltage: <ol style="list-style-type: none"> a) For <i>electricity storage units</i> that are VAR dispatchable, unit terminal voltage, except if the electricity storage units are connected to a common low voltage bus section, then the bus section voltage is adequate for those electricity storage units.

TYPE	SCADA INFORMATION REQUIREMENTS
	<p>3. State of Charge and Charge Limit</p> <p>a) For each <i>electricity storage unit</i> or <i>electricity storage facility</i>, the <i>state of charge</i> of the applicable <i>electricity storage unit</i> or <i>electricity storage facility</i></p> <p>b) For each <i>electricity storage unit</i> or <i>electricity storage facility</i>, the economic maximum charge limit and the economic minimum charge limit expressed in MWh as per the applicable <i>market manual</i>.</p> <p>4. Dynamic Maximum and Minimum Power</p> <p>a) For each <i>electricity storage unit</i> or <i>electricity storage facility</i>, the economic maximum power mode and economic minimum power mode, expressed in MW.</p> <p>5. Base point</p> <p>a) For each <i>electricity storage unit</i> or <i>electricity storage facility</i> associated with a <i>resource</i> providing <i>regulation</i>, the basepoint, if applicable, of the storage unit expressed in MW, according to the applicable <i>market manual</i>.</p> <p>6. Equipment Status</p> <p>a) Automatic Voltage Control and stabilizer status (if applicable) for each <i>electricity storage unit</i> if the status of this equipment is designated by the IESO as required for determination of operating security limits or to maintain reliable operation of the IESO-controlled grid. When applicable, stabilizer status reporting is only required if it can be switched on or off by the <i>market participant</i> operating personnel remotely or at the facility.</p> <p>b) Synchronizing Breaker Status for each <i>electricity storage unit</i>. Where an <i>electricity storage facility</i> is designed such that no low voltage synchronizing breaker is installed for each <i>electricity storage unit</i>, the status of the appropriate HV breaker(s) and disconnect switch(es) normally used to isolate the <i>electricity storage unit</i> must be provided. Where this results in access to the majority of breakers on a bus, the status of the remainder of the breakers shall be provided to complete the bus configuration.</p> <p>Where an <i>electricity storage facility</i> is designed such that there are disconnect switches in parallel, or directly in series, with the synchronizing breaker, the status of those switches is also required.</p> <p>c) <i>Remedial Action Scheme</i> status for each applicable <i>electricity storage unit</i>.</p>
Self-scheduling electricity storage facility with a name-plate rating of less than 10 MW	<p>Monitored Quantities</p> <p>1. Active Power (MW) and Reactive Power (MX) injected or withdrawn:</p> <p>a) The standard requirement for active and reactive power is the provision of <i>net MW</i> and <i>net MX</i> or <i>gross MX</i>. <i>Gross MW</i> and <i>gross MX</i> or <i>net MX</i> are also to be provided, if designated by the IESO as required for:</p> <p>(i) determination of operating <i>security limits</i>;</p> <p>(ii) to maintain reliable operation of the <i>IESO-controlled grid</i>;</p> <p>(iii) for compliance monitoring purposes; or</p>

	SCADA INFORMATION REQUIREMENTS
	<p>(iv) if provision of only the standard requirement values as defined above would have a negative impact on other <i>market participants</i> through reduced operating <i>security limits</i>.</p> <p>b) For <i>electricity storage facilities</i> that have not been aggregated pursuant to Chapter 7 section 2.3:</p> <p>(i) for a group of <i>electricity storage units</i> if those <i>electricity storage units</i> are similar in size and operating characteristics, the standard requirement as defined in part a) shall be provided as a total for these <i>electricity storage units</i>, and total <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a);</p> <p>(ii) if designated by the <i>IESO</i> as required for determination of operating <i>security limits</i> or to maintain reliable operation of the <i>IESO-controlled grid</i> or for compliance monitoring purposes, the standard requirement as defined in part a) for each <i>electricity storage unit</i> shall be provided, and <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> for each <i>electricity storage unit</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a).</p> <p>c) For <i>electricity storage facilities</i> that have been aggregated pursuant to Chapter 7 section 2.3:</p> <p>(i) the standard requirement as defined in part a) shall be provided as an aggregated total, and an aggregated total <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a); or</p> <p>(ii) if so designated by the <i>IESO</i> as required for determination of operating <i>security limits</i> or to maintain reliable operation of the <i>IESO-controlled grid</i> or for <i>dispatch</i> compliance monitoring purposes, the standard requirement as defined in part a) for each <i>electricity storage unit</i> shall be provided, and <i>gross MW</i> and <i>gross MX</i> or <i>net MX</i> for each <i>electricity storage unit</i> shall be provided if designated by the <i>IESO</i> as required using the criteria listed above in part a).</p> <p>2. Voltage:</p> <p>a) For <i>electricity storage units</i> that are VAR dispatchable, unit terminal voltage, except if the <i>electricity storage units</i> are connected to a common low voltage bus section, then the bus section voltage is adequate for those <i>electricity storage units</i>.</p> <p>3. State of Charge and Charge Limit</p> <p>a) For each electricity storage unit or electricity storage facility, the state of charge of the applicable <i>electricity storage unit</i> or <i>electricity storage facility</i></p> <p>b) For each <i>electricity storage unit</i> or <i>electricity storage facility</i> the economic maximum charge limit, the economic minimum charge limit expressed in MWh</p>

TYPE	SCADA INFORMATION REQUIREMENTS
	<p>4. Dynamic Maximum and Minimum Power</p> <p>a) For each <i>electricity storage unit</i>, the economic maximum power mode and economic minimum power mode, expressed in MW.</p> <p>5. Base point</p> <p>a) For each <i>electricity storage unit</i> associated with a <i>resource</i>, providing <i>regulation</i> the basepoint of the applicable <i>electricity storage unit</i> expressed in MW according to the applicable <i>market manual</i>.</p> <p>6. Equipment Status</p> <p>a) Automatic Voltage Control status and Stabilizer status (if applicable) for each <i>electricity storage unit</i> if the status of this equipment is designated by the <i>IESO</i> as required for determination of operating <i>security limits</i> or to maintain reliable operation of the <i>IESO-controlled grid</i>. When applicable, stabilizer status reporting is only required if it can be switched on or off by <i>market participant</i> operating personnel remotely or at the <i>facility</i>.</p> <p>b) Synchronizing Breaker Status for each <i>electricity storage unit</i>. Where an <i>electricity storage facility</i> is designed such that no low voltage synchronizing breaker is installed for each <i>electricity storage unit</i>, the status of the appropriate HV breaker(s) and disconnect switch(es) normally used to isolate the <i>electricity storage unit</i> must be provided. Where this results in access to the majority of breakers on a bus, the status of the remainder of the breakers shall be provided to complete the bus configuration.</p> <p>Where an <i>electricity storage facility</i> is designed such that there are disconnect switches in parallel, or directly in series, with the synchronizing breaker, the status of those switches is also required.</p> <p>c) <i>Remedial Action Scheme</i> status for each applicable <i>electricity storage unit</i>.</p>
Small electricity storage facility	None
Minor electricity storage facility that is embedded in a distribution system and registered as a dispatchable electricity storage participant	<p>Monitored Quantities</p> <p>1. Total active power (MW) output of the individual <i>electricity storage unit</i> or of the aggregated resource.</p> <p>a) Unit status if the <i>facility</i> is comprised of a single <i>electricity storage unit</i>.</p> <p>b) Aggregated resource status if the <i>facility</i> is comprised of aggregated resources, i.e. if at least one unit of the aggregated resource is synchronized, the aggregated resource is synchronized or if no unit in the aggregated resource is synchronized, the aggregated resource is not synchronized.</p> <p>c) Reactive Power (MX) output, if requested by the <i>IESO</i> for reliable operation of the <i>IESO-controlled grid</i>, of individual <i>electricity storage units</i> or of the aggregated resource.</p> <p>d) Unit terminal voltage (kV) if requested by the <i>IESO</i> for reliable operation of the <i>IESO controlled grid</i></p>

TYPE	<u>SCADA</u> INFORMATION REQUIREMENTS
	<ol style="list-style-type: none"> 2. State of Charge and Charge Limit <ol style="list-style-type: none"> a) For each electricity storage unit or electricity storage facility, the state of charge of the applicable electricity storage unit or electricity storage facility expressed as a percentage b) For each <i>electricity storage unit</i> or <i>electricity storage facility</i>, the economic maximum charge limit, the economic minimum charge limit expressed in MWh 3. Dynamic Maximum and Minimum Power <ol style="list-style-type: none"> a) For each <i>electricity storage unit</i> or <i>electricity storage facility</i>, the economic maximum power mode and economic minimum power mode, expressed in MW. 4. Base point <ol style="list-style-type: none"> a) For each <i>electricity storage unit</i> or <i>electricity storage facility</i> associated with a <i>resource</i>, providing <i>regulation</i>, the basepoint, if applicable, of the <i>electricity storage unit</i> expressed in MW according to the applicable <i>market manual</i>.



Type	Synchrophasor Data Requirements
<u>Electricity storage facility</u>	<p>For all three phases the voltage and current phasor measurements and frequency measurements, as further described in the applicable <i>market manual</i>, shall be required for each <i>electricity storage unit</i> as outlined below;</p> <ol style="list-style-type: none">1. For all <i>electricity storage units</i> with a name-plate rating at greater than 20 MVA, measured from the <i>electricity storage facility</i> side of the <i>connection point</i> to the <i>IESO-controlled grid</i>.2. For all <i>electricity storage units</i> connected to the <i>IESO-controlled grid</i> through a common <i>connection point</i> whose aggregate name-plate rating size is greater than 20 MVA, measured from the <i>electricity storage facility</i> side of the <i>connection point</i> to the <i>IESO-controlled grid</i>3. For all <i>electricity storage units</i>, regardless of rated size, that are associated with, or have the potential to, impact an Interconnection Reliability Operating Limit, measured from the terminals defining the Interconnection Reliability Operating Limit.1-4. Notwithstanding the foregoing, a <i>market participant</i> is not required to measure and provide such data when exempted from such requirement as determined in accordance with the applicable <i>market manual</i>.